

.....[®]
CALRAD
ELECTRONICS

819 N. Highland Ave.
 Los Angeles, CA 90038

Tel (323) 465-2131, Fax (323) 465-3504
 Visit us on the web at www.calrad.com

New Part No. **15-133**
4 Channel Stereo
Headphone Amplifier



Calrads new headphone distribution amplifier allows low or line-level sources to drive up to 6 pairs of stereo headphones. 6 separate amplifiers drive any mix of headphones from 8 to 600 ohms and each headphone has its own stereo volume control. The rugged steel metal case with rubber end caps makes this unit durable for any environment.

Line or Headphone Input



Adapter Included

1



Headphones 1

2



Headphones 2

3



Headphones 3

4



Headphones 4

Specifications:

Input Impedance: 100K Ohms unbalanced
 Output Impedance drives 8 Ohms, 32 Ohms, 600 Ohms
 Max Input Level: +14 dBV Input
 Input/Output Connectors: (5) Stereo 1/4 in. TRS phone jacks.
 Max Gain: 20 dB/Channel
 S/N Ratio: >90 dB
 THD: <.008 IMD (SMPTE) <.008
 DC Power: 12Vdc, 300ma
 Weight: 1 lb (.45 kg)
 Size: 3 x 5 x 1.25 in. (8 x 12.7 x 3.2cm)

Optional Accessories:

35-550

Stereo 1/4" Male Plug
 to 1/8" Female Jack



55-899-6S

Stereo 1/4" Male Plug
 to RCA Male Jacks, 6 ft.

